


# PT06 SE (MS3126)

## SP06 SE

### straight plug




“SE”, MS / “E” Open Wire Seal




PT06SE-XX-XXX  
 SP06SE-XX-XXX  
 PTG06SE-XX-XXX  
 MS3126E-XX-XXX

TERMINATION ASSEMBLIES  
 “SE” (SR), MS / “F” Strain Relief



PT06SE-XX-XXX (SR)  
 SP06SE-XX-XXX (SR)  
 PTG06SE-XX-XXX (SR)  
 MS3126F-XX-XXX (SR)

“SP”, MS / “P” Potting Boot



PT06SP-XX-XXX  
 SP06SP-XX-XXX  
 PTG06SP-XX-XXX  
 MS3126P-XX-XXX

To complete part number see how to order on page 32.

Shell Size	Plug Front View		Plug Side View								
	S Dia. Max.	Z ±.045	Z' ±.045	Class “SE”, MS / “E”		Class “SE” (SR), MS / “F”			Class “SP”, MS / “P”		
				L Max.	N Max.	G Dia.	L Max.	N Max.	D Dia.	L Max.	N Dia. Max.
8*	.734	.640	.579	1.328	.540	.125	2.413	.828	.327	1.750	.578
10	.859	.640	.579	1.328	.685	.188	2.413	.891	.444	1.750	.734
12	1.031	.640	.579	1.328	.813	.312	2.413	1.016	.558	1.750	.858
14	1.156	.640	.579	1.328	.930	.375	2.413	1.141	.683	1.750	.984
16	1.281	.640	.579	1.328	1.057	.500	2.528	1.203	.808	1.750	1.110
18	1.391	.640	.579	1.328	1.175	.625	2.528	1.469	.909	1.750	1.234
20	1.531	.640	.579	1.297	1.301	.625	2.753	1.469	1.034	1.750	1.360
22	1.656	.640	.579	1.297	1.428	.750	2.753	1.656	1.159	1.750	1.484
24	1.777	.640	.579	1.359	1.533	.800	2.830	1.750	1.284	1.766	1.610

\* PT-SE, MS-SE and MS-SP only.  
 All dimensions for reference only.

# Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

## Amphenol:

[MS3126F22-55S](#) [MS3126E10-6S](#) [MS3126E12-10P](#) [MS3126E12-10S](#) [MS3126E14-19P](#) [MS3126E14-19S](#)  
[MS3126E16-23S](#) [MS3126E20-39P](#) [MS3126E22-41P](#) [MS3126E8-33S](#) [MS3126E8-33SW](#) [MS3126F10-6P-LC](#)  
[MS3126F10-6SW](#) [MS3126F12-10PW](#) [MS3126F12-10SW](#) [MS3126F12-3P](#) [MS3126F12-3S](#) [MS3126F12-8P](#)  
[MS3126F12-8S](#) [MS3126F14-12P](#) [MS3126F14-15S](#) [MS3126F14-18PW](#) [MS3126F14-18S](#) [MS3126F14-18SW](#)  
[MS3126F14-19P](#) [MS3126F14-19S](#) [MS3126F14-19SX](#) [MS3126F14-5P](#) [MS3126F14-5S](#) [MS3126F16-26P](#)  
[MS3126F16-8S](#) [MS3126F18-32P](#) [MS3126F18-32S](#) [MS3126F20-41S](#) [MS3126F24-61P](#) [MS3126F24-61S](#)  
[MS3126P14-19S](#) [MS3126F24-61PW](#) [MS3126E12-8PX](#) [MS3126E14-18PW](#) [MS3126E14-18PZ](#) [MS3126E14-18SW](#)  
[MS3126E14-18SX](#) [MS3126E14-19SX](#) [MS3126E14-19SY](#) [MS3126E14-5PX](#) [MS3126E16-26SW](#) [MS3126E20-39PX](#)  
[MS3126E24-61PW](#) [MS3126F12-8PZ](#) [MS3126F14-18PX](#) [MS3126F14-18PY](#) [MS3126F16-8SW](#) [MS3126F22-21SW](#)  
[MS3126P10-6PW](#) [MS3126F16-26SW](#) [MS3126P14-18S](#) [MS3126F16-26P-LC](#) [MS3126F14-19S-LC](#) [MS3126E20-41P](#)  
[MS3126F22-55SY](#) [MS3126F22-41SX](#) [MS3126F22-41SW](#) [MS3126F22-41PY](#) [MS3126F22-41PW](#) [MS3126F14-15PY](#)  
[MS3126F14-15PX](#) [MS3126F22-41PX](#) [MS3126E12-8PW](#) [MS3126E20-41SX](#) [MS3126E22-21S](#) [MS3126F14-12SX](#)  
[MS3126F14-15SZ](#) [MS3126F14-18SX](#) [MS3126F14-18SY](#) [MS3126F14-18SZ](#) [MS3126F14-19PW](#) [MS3126F14-19SY](#)  
[MS3126F14-5SX](#) [MS3126F22-55PX](#) [MS3126F22-55SX](#) [MS3126F24-61SW](#) [MS3126F12-8PY](#) [MS3126E18-32SY](#)  
[MS3126F18-32PX](#) [MS3126F16-23P](#) [MS3126F16-26PW](#) [MS3126P20-41SX](#) [MS3126P20-39S](#) [MS3126F16-99S](#)  
[MS3126F14-18PX\(LC\)](#) [MS3126E18-30P](#) [MS3126F18-11PZ](#) [MS3126F20-41P\(LC\)](#) [MS3126F16-8PZ](#) [MS3126F22-](#)  
[55P\(LC\)](#) [MS3126F24-61P\(LC\)](#) [MS3126F20-39S\(LC\)](#) [MS3126F16-99S\(LC\)](#) [MS3126E20-41P\(LC\)](#)